

Ty¹DP vvv² iii³

2 or 3 Channel High Voltage Desk Top Power Supply

¹y = number of channels
²v = voltage code
³i = current code

Operators Manual

Contents:

1. General information
2. Technical Data
3. Front panel
4. Operation
5. Polarity setting
6. Control via RS232/USB Interface

WARNING!

-It is not allowed to use the unit if the covers have been removed.

- It is not allowed to connect or disconnect the HV cable if HV is ON !

-We decline all responsibility for damages and injuries caused by an improper use of the module. It is highly recommended to read the operators manual before any kind of operation.

Note

The information in this manual is subject to change without notice. We take no responsibility for any error in the document. We reserve the right to make changes in the product design without reservation and without notification to the users.

Filename TyDPvviii_USB_eng.____; Version 3.00 as of 09-08-25

1. General information

The model TYDP **vvv iii** is a high voltage desk top supply which offer a very stable output voltage up to 6 kV for use in industry and research. The output is generated by means of a high voltage module of the DPS-series, which is supplied by means of an AC/DC converter.

Main Characteristics:

- High voltage desk top power or 19 inch rack supplies with either front-panel or remote control via analogue I/O
- Output voltages with low ripple and noise
- Compact and ruggedized enclosure
- Output short circuit and overload protected
- Control manually, via analogue I/O and USB Interface

2. Technical Data

T3DP vvv² iii³ EPU	² 005 ³ 106	² 010 ³ 106	² 020 ³ 605	² 030 ³ 405	² 040 ³ 305	² 050 ³ 205	² 060 ³ 155
Output voltage V_{Onom}	500 V	1 kV	2 kV	3 kV	4 kV	5 kV	6 kV
Output current I_{Onom}	10 mA	10 mA	6 mA	4 mA	3 mA	2 mA	1,5 mA
Polarity	positive or negative, switchable manually or electronically at $V_{OUT} = 0$ with option EPU						
Ripple & noise	typ. < 2 mV _{P-P} , max. 7 mV _{P-P}						
Stability: $\frac{\Delta V_O}{\Delta V_{INPUT}}$	< $1 * 10^{-5}$						
ΔV_O (no load to full load)	< $5 * 10^{-5}$						
Temperature coefficient	< $5 * 10^{-5}/K$						
Voltage measurement	Resolution:	$V_{Onom} < 1$ kV: 0,1 V ; $V_{Onom} \geq 1$ kV: 1 V / 4-digit LCD display					
	Accuracy:	$\pm (1\% * V_{Onom})$ (for one year)					
Voltage setting	manual:	via 10-turn potentiometer (" LOC ")					
	REMOTE:	via analog I/Omit $V_{SET/MON} = 0$ bis 5 V (" REM ") oder USB (" USB ")					
Current measurement	Resolution:	$I_{Onom} \geq 10$ mA: 10 μ A ; $I_{Onom} < 10$ mA: 1 μ A / 4-digit LCD display					
	Accuracy:	$\pm (1\% * I_{Onom})$ (for one year)					
Current setting	manual:	via 10-turn potentiometer (" LOC ")					
	REMOTE:	via analogue I/O with $V_{SET/MON} = 0$ to 5 V (" REM ") or USB (" USB ")					
Rate of change of V_O	fixed: $V_{Onom} / 4s$ (at HV-ON/OFF)						
Protection	Output short circuit and overload protected. Attention ! There is only one short circuit or arc per second allowed! The integral output current must limited to the max. output current of the module external otherwise.						
Remote control	via analog I/O or USB interface						
Line voltage AC (V_{INPUT})	100 to 240 V-AC; 50/60 Hz; fused with 2 A-slow						

Connectors	HV output: analogue I/O: USB:	SHV-Connector on the rear 9-pin male D-Sub connector on the rear on the rear
Desk case	Size (W/H/D) : (19 inch / 2U = 88.90 mm / 305mm)	
Operating temperature	0 ... +50 °C	
Storage temperature	-20 ... +60 °C	
9-pin male D-Sub connector "analog I/O" on the rear side		
PIN	Name	Description
1	n.c.	
2	V_I _{MON}	Monitor voltage corresponding I _O : I _O = 0 to I _{Onom} ⇒ V ₂₋₆ = 0 to 5 V (R _i = 10 kΩ)
3	INH	INHIBIT (TTL level, LOW ⇒ V _O = 0, [LOW to] HIGH or open ⇒ V _O = V _{SET} with ramp)
4	V_I _{SET}	Setting current (R _{IN} = 10 kΩ): V ₄₋₆ = 0 to 5 V ⇒ I _O = 0 to I _{Onom} ± 1% n.c. ⇒ I _{Onom} is possible
5	V_Pol	Setting polarity only with option EPU : (TTL level, LOW ⇒ negative, HIGH ⇒ positive)
6	GND	GND = V _{SET_0V} Signal 0 V (connected to the metal module box)
7	V_V _{MON}	Monitor voltage corresponding V _O : V _O = 0 to V _{Onom} ⇒ V ₇₋₆ = 0 to 5 V (R _{OUT} = 10 kΩ)
8	V_V _{SET}	Setting voltage: V ₈₋₆ = 0 to 5 V (R _{IN} ≈ 300kΩ) ⇒ V _O = 0 to V _{Onom} ± 1%
9	V _{REF}	V ₉₋₆ = 5 V (1 mA) Reference voltage for a external potentiometer (Sliding contact on V_V _{SET} and/or V_I _{SET})

Operation see in the attached description